

LMS8-A Mini Switch

Installation Guide



LMS8-A Mini Switch

The Lantronix LMS8-A Mini Switch brings the performance advantages of Ethernet switching to the workgroup. The advantages include:

1. Separate Ethernets on each port - where hubs provide only a single shared 10 Mbps segment, the LMS8-A provides up to 8 separate Ethernets, each capable of supporting a full 10 Mbps of throughput
2. Collision domain separation - reduces unnecessary traffic on each segment and filters out bad packets
3. Full duplex capability for each port
4. Optional AUI port allows compatibility with other 10 Mbps Ethernet media

The LMS8-A has 8 10 Mbps RJ45 ports with an optional AUI interface available on Port 1. Each port is capable of supporting half or full duplex mode. LMS8-A is a self-learning bridge, capable of supporting 8,192 addresses and performing wirespeed filtering and forwarding. All bridging functions are automatic - no management software is required. Simply install the LMS8-A into your workgroup network and you can immediately enjoy the benefits of Ethernet switching.

Installation Tips

Note: These tips are additional to the Installation Instructions that can be found on the back of the unit.

- ▼ All ports on the LMS8-A can support full duplex operation - please make sure that each port has the proper switching setting for the desired modes (default switch settings are for half duplex). When the unit is powered on, verify the correct modes of operation by examining the LEDs for each port. No further configuration is necessary. If the correct mode of operation does not appear in the LED display, check the cable and connecting equipment. If changes are made, power the unit off and then on again to reset.
- ▼ Use of the optional AUI on Port 1 will negate the ability to use the RJ45 for that port.
- ▼ If the Link/Duplex LED for a port is not lit, please check the cable being used. The port will only be operational if the LED is green (Good Link/Half Duplex) or yellow (Good Link/Full Duplex).

Power Requirements

The Lantronix LMS8-A is shipped with either a 120VAC (-01 version) or a 220VAC (-02 version) power supply. Input power requirements are 15 volts at 1.0 Amps.

CAUTION:

Not for installation in air ducts or plenums or other environmental air handling spaces. Changes or modifications to this device not explicitly approved by Lantronix will void the user's authority to operate this device.

Cable Requirements

The Lantronix LMS8-A is compatible with UTP (unshielded twisted pair) and STP (shielded twisted pair) cables. EIA category 3,4 or 5 cables can be supported on the RJ45 connectors.

All ports of the LMS8-A are configured as MDI-X ports; Port 2 has an MDI option for connecting to hubs, repeaters or other switches.

The following cable configuration is suggested for the cables attached to an LMS8-A:

	LMS8-A	End nodes	MDI-X ports	MDI ports
Pin 1	TD+	TD+	RD+	TD+
Pin 2	TD-	TD-	RD-	TD-
Pin 3	RD+	RD+	TD+	RD+
Pin 6	RD-	RD-	TD-	RD-

1. The cable between the LMS8-A and an end-node or another switch is straight through.
2. The cable between the LMS8-A and a hub or repeater is not straight through but rather a "crossover" (transmit pairs and receive pairs are reversed). By selecting the MDI option (when available), a straight through cable can be used.

Technical Support

If problems occur during product operation, please check the LMS8-A switch settings, cables, connectors, network terminators, hardware compatibility and other network components first.

Prior to contacting Lantronix Technical Support, please have the following information available:

- Model number and serial number
- Purchase date
- Network configuration
- Definition of the problem encountered

Lantronix Technical Support can easily be reached at our worldwide website at www.lantronix.com. The website contains technical tips and other helpful product information.

Lantronix Technical Support can also be reached via email at support@lantronix.com, or via telephone between the hours of 6:00 a.m. and 5:30 p.m. (PST) at 800-422-7044 (USA) or 949-453-3990 outside of the United States.

Your Lantronix LMS8-A Mini Switch is covered by a five-year limited warranty.

WARNING!

This device complies with part 15 of the FCC rules. Operation is subject to the following restrictions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including that which may cause undesired operation. Operation of this equipment in a residential area is likely to cause interference in which case the user, at his or her own expense, will be required to take whatever measures may be required to correct the interference.

NOTE: The RJ45 ports are not for telephone use!

Declaration of Conformity

(according to ISO/IEC Guide 22 and EN 45014)

Manufacturer's Name: Lantronix
Manufacturer's Address: 15353 Barranca Parkway
Irvine, CA 92618 USA

declares, that the product:

Product Name: Micro Switch
Model Number(s): LMS8-A

conforms to the following standards:

Safety: EN 60950:	1988 + A1, A2
EMC: EN 55022:	1988 Class A
EN 50082-1:	1992
IEC 801-2:	1991/prEN55024-2: 1992-4kV CD, 8kV AD.
IEC 801-3:	1992/prEN55024-3: 1991-3V/m
IEC 801-4:	1988/prEN55024-4: 1992-.05kV Signal Lines 1kV Power Lines

Supplementary Information:

"The product complies with the requirements of the Low Voltage Directive 73/23/EEC and the EMC Directive 89/336/EEC."

Manufacturer's Contact: Director of Quality Assurance
Lantronix
15353 Barranca Parkway
Irvine, CA 92618 USA
Tel: 949-453-3990
Fax: 949-453-3995

The logo for Lantronix, featuring the word "LANTRONIX" in a bold, sans-serif font. The letters are white with a dark, textured shadow behind them, giving it a three-dimensional appearance. The background of the logo is a dark, irregular shape that looks like a splash or a brushstroke.

Part No. 900-115

15353 Barranca Parkway, Irvine, CA 92618
949-453-3990 ▼ Fax: 949-453-3995
Direct Sales: 800-422-7055 ▼ sales@lantronix.com
International Sales: 949-450-7227 ▼ intsales@lantronix.com
Tech Support: 800-422-7044 ▼ support@lantronix.com
www.lantronix.com



Important Instructions For LMS and LFX Installation

- ▼ **Design connections to avoid loops - these unmanaged switches do not support Spanning Tree Algorithm**
- ▼ **If using dedicated switch ports for a connection to a single server, single user or another switch, use full duplex if possible for much better performance**
- ▼ **If using 10BASE2, consider using a repeater connected to a LMS/LFX 10BASE-T port instead of a transceiver, or contact Lantronix for more information**
- ▼ **Avoid bottlenecks in network design by attaching servers to the same switch as their most common clients**
- ▼ **Try to configure each side of the extender/bridge so that nodes that will communicate frequently are on the same port**
- ▼ **To extend 100BASE-FX fiber to maximum length, use 2 LFX2-MAs (with 100BASE-FX fiber transceivers) connected by a Category 5 cable; this allows both fiber links to be extended to the 412 meter limit (each LFX2-MA extender/switch regenerates the signal)**
- ▼ **Because it is a store-and-forward device, the LFX2 filters out bad packets from attached network segments, so it can be used as a screen between a problem segment and the network backbone**

15353 Barranca Parkway Irvine California 92618 sales@lantronix.com
949-453-3990 Fax: 949-453-3995 1 800-422-7055